

CONTRACTOR:	
PROJECT:	DATE:
PREPARED BY:	MODEL: RV OUTLET BOX

### **SPECIFICATION & FEATURES**

RV Outlet Box 50A Rated UL Listed NEMA 14-50R Receptacle NEMA3R/ IP 32 Rated Enclosure

RV Power Outlet Box comes ready to use with no need to assemble individual parts, saving installation time. The single, heavy-gauge NEMA 3R rainproof enclosure protects against weather and vandalism.



## **CERTIFICATIONS/WARRANTY**

### Warranty

Guaranteed for one year from the purchase date of the product, against mechanical defects in manufacturing.

### Listings

UL Listed NEMA 14-50R Receptacle NEMA3R/ IP 32 Rated Enclosure

# **CONSTRUCTION**

MATERIAL	SIZE	COLOR
Metal	7x5x6"	Grey
MOUNTING	KNOCKOUTS	AMPERAGE
Surface Mounted	6	50
	Metal Mounting	Metal 7x5x6"  MOUNTING KNOCKOUTS

**NEMA** 

14-50R





CONTRACTOR:	
PROJECT:	DATE:
PREPARED BY:	MODEL:

### **INSTALLATION**

### USED WITH 30AMP/50AMP UL&CUL LISTED FLUSH MOUNT RECEPTACLES


For use with copper or aluminum wire Connect line wires to proper terminals on receptacle

### INSTALLATION

- 1. Loosen screw of the surface, remove the cover.
- 2. Remove cable knockouts and install cable clamp or conduit connector.
- 3. Pass the wires thru the cable clamp. strip wires as required (1/2 inch).
- 4. Refer to the figure on the right for wiring, connect wires to proper terminals on receptacle, tighten each terminal screw.
- 5. Assemble receptacle with box cover.
- 6. Install the cover and tighten the screw.

#### CAUTION!!!

RISK OF FIRE, SHOCK OR DEATH, TURN OFF CIRCUIT BREAKER BEFORE INSTALLATION.



## **ORDERING INFORMATION**

Part Code	IMS Code
RVPWRB50	0586-5408